

Product data sheet



Presence detector



Reference number

3361-1 WW

Presence detector

with integrated BCU

ETS product family: Physical sensors

Product type: Movement

Intended use

- Requirement-oriented control of lighting, room thermostats and other electrical loads in interior rooms
- Ceiling mounting on fixed ceilings in appliance box according to DIN 49073 or surface-mounted housing ref.-no.: PM-KAPPE-1 or PM-KAPPE AL-1

Product characteristics

- Integrated bus coupling unit
- 3 PIR sensors
- Detection field 360° (3 x 120°)
- Integrated brightness sensor
- Deployed as presence detector, motion detector, or for alert operation
- Output functions: Switching, staircase function, switching with forced position, value transmitter, light scene extension, operating mode setting for room temperature controller
- Detection area extendible by parallel switching of several devices as main unit or extension unit
- Manual sensitivity adjustment
- Status LED: Flashes during motion detection; depending on programming in normal operation or only during the walking test mode

Additional characteristics of "Universal" version:

- Manual operation with IR remote control possible (ref.-no.: KNX PM FB IR)
- 5 function blocks for motion or presence detection each with 2 outputs
- Function blocks switchable, e.g. for day/night operation
- PIR sensors can be evaluated separately
- Brightness sensor function with 3 limiting values
- Light control with max. 3 channels, setpoint shift in operation, separate configuration of dimming-up, control and dimming-down phase
- Light control can be combined with presence detector function

Presence detector function:

- Detection of the smallest motions e.g. at a workplace for detecting the presence of persons
- Switch on: Motion detection and brightness threshold not reached
- Switch off: No motion in the detection field and shut-off delay elapsed or brightness threshold exceeded

Motion detector function:

- Motion detection for passageways in buildings
- Switch on: Motion detection and brightness threshold not reached
- Switch off: No motion in the detection field and shut-off delay elapsed

After reacting and switching on, the motion detection works independently of the brightness.

Signalling mode:

- Brightness-independent detection of motions in the detection field
- Switch on: After detection of an adjustable number of motions within the set monitoring period
- Switch off: No persons in the detection field and shut-off delay elapsed

Accessories:

protection cage ref.-no.: SK 180-90 WW

Accessories:

surface-mounted housing ref.-no.: PM-KAPPE-1, PM-KAPPE AL-1

Technical data

Rated voltage KNX:	DC 21 ... 32 V SELV
Current consumption KNX:	max. 12.5 mA
Connection bus:	terminal
Ambient temperature:	-5 ... +45 °C
Storage/transport temperature:	-25 ... +70 °C
Relative humidity:	5 ... 93 % (no condensation)
Protection class:	III
Detection angle:	360°
Range:	Ø approx. 20 m (mounting height 3 m)
Brightness sensor	
Measuring range:	0 ... 2000 lx
Detection range:	Ø 2 m

Universal

Colour:

white