



3873P01

RXB

## Room controllers

**RXB21.1  
RXB22.1**

For fan-coil applications FC-10, FC-11, FC12  
with Konnex bus communications (S-mode and LTE mode)

The RXB21.1 and RXB22.1 room controllers are used for temperature control in individual rooms.

- For 2-pipe or 4-pipe fan-coil systems, with or without change-over
- PI control
- Konnex bus communication (S-mode and LTE mode)
- Integration into the DESIGO building automation and control system via PX KNX
- Integration into Syncro
- Control of AC 24 V PDM<sup>1)</sup> thermic valve actuators, 3-position AC 24 V motorized valve and damper actuators, or electric heating coils
- Use of motorized KNX / EIB bus valves
- Volt-free relay contacts for control of fans and electric heating coils
- Commissioning with ETS3 Professional, Syncro ACS or "HandyTool"
- AC 230 V operating voltage
- Plug-in screw terminals

1) PDM = Pulse Duration Modulation

## Application

---

The RXB21.1 and RXB22.1 room controllers are optimized for control of fan-coil systems in individual rooms.

The following options are available with fan-coil systems:

- RXB21.1: Single-speed to 3-speed automatic fan control
- RXB22.1: Single-speed to 3-speed automatic fan control with integrated relay for electric re-heater

The application of each controller is determined by the application software.

The controllers are delivered with a fixed set of applications, each of which contains various individual applications. The relevant application is selected and activated during commissioning using one of the following tools:

- ETS3 Professional (EIB / KNX Tool Software)
- Syncro ACS
- "HandyTool" (the QAX34.3 room unit includes a tool function allowing you to parameterize the connected RXB controller).

### Use of spare inputs/outputs

Some of the applications do not make full use of all the inputs and outputs. These I/Os can be used freely in conjunction with a building automation and control system to register digital signals, for example, or to control various items of equipment (ON/OFF or pulse control with AC 24 V or volt-free relay contacts).

The inputs can then be read and the outputs controlled via the building automation and control system.

Note      Not suitable for time-critical processes <1 s.

## Functions

---

The room controller functions are determined by the selected application and its parameters, and by the input/output configuration.

For details, refer to the FNC description of functions, document CA110385.

When DESIGO RXB controllers are integrated into a building automation and control system, or into a Syncro system, additional functions become available such as time scheduling, central control of setpoints, etc.

## Applications

---

The following applications are available for the RXB2... room controllers:

Application group (type)	Fan-coil applications
<b>FC-10 (with RXB21.1)</b>	FNC02 2-pipe system with changeover FNC04 4-pipe system FNC08 4-pipe system and room/supply air cascade control FNC20 4-pipe system with single damper control
<b>FC-11 (with RXB21.1)</b>	FNC10 2-pipe system with changeover and outside air damper FNC12 4-pipe system with outside air damper FNC18 2-pipe system with changeover and radiator
<b>FC-12 (with RXB22.1)</b>	FNC03 2-pipe system with changeover and electric re-heater FNC05 4-pipe system with electric re-heater

Note Only one application at a time can be activated with the tool (ETS3 Professional, Syncro ACS or "HandyTool").

---

## Types

The RXB21.1 and RXB22.1 room controllers differ only in the number of outputs available:

Type	AC 24 V triac outputs	Relay outputs
<b>RXB21.1</b>	For 2 thermic valve actuators or two 3-position actuators	For 3-speed fan control
<b>RXB22.1</b>	For 2 thermic valve actuators or one 3-position actuator	<ul style="list-style-type: none"><li>• For 3-speed fan control</li><li>• internal relay for electric heating coil</li></ul>
<b>RXZ20.1</b>	Accessories: Terminal covers	

---

## Ordering

When ordering please specify the quantity, product name, type code and application group.

Example: 30      Room controllers, type RXB21.1/FC-10


## Compatibility

The RXB2... room controller is compatible with field devices from Siemens Building Technologies and with KNX / EIB-compatible third-party devices.

For details, refer to the DESIGO RX hardware overview, CA2N3804.

## Design

The RXB2... controllers consist of a housing base, a housing cover and the printed circuit board with connection terminals. The controllers also have a tool socket, a service LED and a programming pin.



### Service LED

The programming LED shows the operational status of the room controller as follows:

Green flashing	OK, device is in operation
Red ON	<ul style="list-style-type: none"><li>Addressing mode (ACS / ETS)</li><li>Fault</li></ul>
Orange / green flashing	Parameter download
OFF	<ul style="list-style-type: none"><li>No supply voltage</li><li>Fault</li><li>Service LED disabled by software</li></ul>
Other patterns	<ul style="list-style-type: none"><li>Start-up (approx. 5.sec)</li><li>Fault</li></ul>

### Programming pin

The programming pin is used to identify the controller in the commissioning phase.

Pressing this pin causes the red programming LED to light up and remain on until identification of the controller is complete.

Once the programming pin has been pressed, the tool overwrites the hardware address in the room controller.




If there are no terminal covers fitted, the programming pin may be operated only by a qualified electrician.


**The adjacent terminal may be a live mains voltage conductor.**

## Terminal cover

Terminal covers (RXZ20.1) are available as an option, to protect the connection terminals from physical contact and dirt. The programming LED remains visible when the terminal covers are in place, and the programming pin can be operated with a pointed implement. The cable is connected to the room controller by breaking out the perforated cable entry guide.



## Label (example for RXB21.1)



### Note

Options for use of the labeling fields “Appl.” and “Loc.”:

- Handwritten identification of the location and the activated application group.

## Connection terminals

All terminals are detachable plug-in screw-terminals. To avoid incorrect wiring, terminals which can be connected to AC 230 V (relay outputs) are physically separate from the other terminals.




### Note!

The cable restraints on the housing base *must* be used for the connections to terminals 19 ... 28 (AC 230 V). The conductors must be secured with cable ties (see diagram).



### Warning!

**Ensure that the power is off before inserting or removing plug-in terminals connected to a mains voltage.**



## Communication

The RXB2... controllers communicate with other devices via the following interfaces:

- PPS2 interface (proprietary) for the exchange of data with the room units
- KNX / EIB bus (terminals CE+ and CE-) for communication with:
  - PX/KNX interface (to DESIGO INSIGHT)
  - Interface OCI700 (to Synco)
  - Other DESIGO RXB controllers
  - KNX / EIB compatible field devices (e.g. temperature sensor)




The tool socket (RJ45) must be connected only by a qualified electrician. The adjacent terminal may be a live mains voltage conductor.

## Connecting the tool

To facilitate commissioning, the tools ETS3 Profession or Synco ACS can be connected at three different points (marked **(A)** in the diagram) in the plant:

- to the KNX / EIB bus cable at any point
- to the RXB2... controller (RJ45 tool socket)
- to the room unit (RJ45 tool socket)



### Notes

- The tool socket is a proprietary socket.

A Siemens connecting cable must be used (e.g. PXA-C1).

**When connected to Ethernet, the device on the other end may be damaged!**



### Caution!

- The tools ETS3 and ACS, even if connected to a tool socket, require an interface:
    - RS232 KNX/EIB interface (ETS3)
    - OCI700 USB-KNX / EIB interface (ETS3 , ACS).
  - The "HandyTool" is connected to the tool socket of the room controller or to the tool socket of the room unit (QAX3..., RXZ90.1) (**B**).
  - If you use OCI700 as an interface, it is connected to the service plug of the controller or of the room unit.
- As long as the OCI700 is connected to the service plug, it must be supplied by the computer via the USB interface.** Otherwise the LCD display of the room unit will turn dark and the controller will switch to addressing mode.

## Disposal



The device is classified as waste electronic equipment in terms of the European Directive 2002/96/EC (WEEE) and should not be disposed of as unsorted municipal waste.

The relevant national legal rules are to be adhered to.

Regarding disposal, use the systems setup for collecting electronic waste.

Observe all local and applicable laws.

## Engineering notes

The KNX / EIB Building Services Management Manual and system principles supplement (see "Reference documentation", page 11) contains the information relevant for the engineering of the KNX / EIB bus (topology, bus repeaters, etc.) and for the selection and dimensions of connecting cables for the supply voltage and field devices.

### AC 230 V supply cables

- The RXB2... room controllers operate with a mains supply voltage of AC 230 V. The controlled devices (valves and damper actuators) receive their power directly from the room controller. This means that a separate AC 24 V supply is not necessary for the controllers and associated field devices.
- The sizing and fuse protection of the power supply cables depends on the total load and on local regulations. The power supply cables connected to the room controller must be secured with cable restraints.
- If serial wiring is applied on the terminal block 19/21, the connection will be interrupted if the block is removed from the controller (the jumpers 19-19 and 21-21 are on the PCB, not in the block, see terminal diagrams on pages 11 and 12)
- The supply cables must be secured with cable restraints.

### Volt-free relay outputs AC 230 V

- The volt-free relay outputs allow the switching of loads up to AC 250 V, 5 A (4 A). The heating coil relay in the RXB22.1 switches resistive loads up to 1.8 kW. The cable dimensions depend on the connected load and the local installation regulations.
- The circuits must be externally fused ( $\leq 10$  A) as there are no internal fuses.
- The cables connected to the room controller must be secured with cable restraints.



**Note!**

**The fans must not be connected in parallel.**

### AC 24 V triac outputs

The **simultaneous** load on outputs Y1 ... Y4 must not exceed 9.5 VA.

Example:

Y1 (heating)	2 thermic valve actuators, type STP72E	5 W
Y2 (cooling)	2 thermic valve actuators, type STP72E	5 W
Y3, Y4 (outside air)	3-position damper actuator	4.5 VA

The maximum load is 9.5 VA for the heating sequence and 9.5 VA for the cooling sequence.

This is acceptable because the two sequences never operate at the same time.




**Note!**

With low loads (< 2VA) the voltage tolerance may be greater than +20% (see technical data).

## Mounting instructions

The room controllers can be mounted in any orientation, and fixed as follows:



### Rail mounting

The housing base is designed for snap-mounting on DIN rails, type EN50022-35 x 7.5 (can be released with a screwdriver).

### Surface mounting

There are two drill holes for screw-mounting (see "Dimensions" for drilling template). The housing base is fitted with raised supports. Screws: Max. diameter 3.5 mm, min. length 38 mm



#### Note!

**Tightening torque for fixing screws max. 1.5 Nm**

When mounting note the following:

- The controller should not be freely accessible after mounting. It must be mounted in a cabinet or behind a cover that can only be opened / removed with a key or a tool.
- Ensure adequate air circulation to dissipate heat generated during operation.
- Easy access is required for service personnel
- Local installation regulations must be observed.

Mounting instructions and a drilling template are printed on the controller packaging.

## Commissioning

The RXB2... room controllers are commissioned with either the ETS3 Professional or the Syncro ACS tool

- via the RS232-KNX / EIB interface, or
  - via the USB-KNX / EIB interface (OCI700),
- or with the HandyTool" via PPS2

### Labeling

The definitive application and the controller's location are handwritten in the labeling fields "Appl." and "Loc" in the commissioning stage.

### Function test

A special test mode (ETS3 Professional or "HandyTool") is available for operation of the outputs. Further, if the digital inputs have been activated, they can be interrogated.



## Note!

- In the event of a long-term short circuit (approx. 4 minutes) or overload, the thermal fuse in the transformer may trip. Subsequently, the device must be exchanged.**
- There is no protection against accidental connection on the AC 24 V side.**
- Mains AC 230 V for the supply and for the relays must be disconnected before plugging and unplugging the terminal blocks (danger of electric shock!)**
- If serial wiring is applied on the terminal block 19/21, the connection will be interrupted if the block is removed from the controller (the jumpers 19-19 and 21-21 are on the PCB, not in the block, see terminal diagrams on pages 11 and 12).**

## Technical data

<b>△ Power supply</b>	Operating voltage	AC 230 V ± 10 %
	Rated voltage	AC 230
	Frequency	50/60 Hz
	Power consumption with connected field devices	Max. 12 VA
	Internal fuse	Thermal, non-resetting
<b>Operating data</b>	Control algorithm	PI
<b>Inputs</b>		
Signal inputs D1, D2 (for volt-free contacts)	Quantity	2
	Contact voltage	DC 16 V
	Contact current	DC 5 mA
	Contact transfer resistance	Max. 100 Ω
	Contact insulation resistance	Min. 50 kΩ
	Switch time:	min. 20ms "ON", min. 20ms "OFF"
Measured value input B1	Compatible temperature sensors	LG-Ni 1000
	Quantity	1
	measuring range	0 ... 50 °C
	Sensor current	0.5 mA
	Resolution	0.1 K
	Measuring error at 25 °C sensor temp. (without cable)	max. 0.5 K
<b>Outputs</b>		
AC24 V triac outputs , Y1 ... Y4	Quantity	2 (RXB22.1) 4 (RXB21.1)
	Output voltage	AC 24 V ON/OFF, PWM or 3-position: +/-20% <b>(May exceed +20% with loads under 2VA)</b>
	Output current	Max. 0.5 A
	Total nominal load (at both outputs simultaneously)	Max. 9.5 VA (e.g. 2 thermic valves, type STP72E per heating and cooling sequence + 1 damper actuator 4.5 VA)
<b>△ Relay outputs Q14, Q24, Q34</b>	Quantity	3
	Relay type	Monostable
	Contact rating with AC voltage	
	Switching voltage	Max. AC 250 V, min. AC 19 V
	Nominal current, resistive/inductive	Max. AC 5 A/4 A ( $\cos \varphi = 0.6$ )
	Making current 200 ms half-time	Max. 20 A
	Switching current at AC 29 V	Min. AC 10 mA
	Contact rating with DC voltage	
	Switching voltage	Max. DC 250 V, min. DC 5 V
	Switching current at DC 5 V	Min. DC 100 mA
	Switching capacity	Max. 20 W
	Inductive load L/R	Max. 7 ms
Q44	Relay type	Monostable
	Contact rating with AC voltage	
	Max. admissible load (resistive only)	Max. 1.8 kW
	External fuse (essential)	Max. 10 A


Ports/interfaces				
Interface to room unit	Number of room units connectable	1		
	Interface type for room unit	PPS2		
	for ETS3 Professional / ACS	KNX / EIB bus		
	PPS2 baud rate	4.8 kbit/s		
	Baud rate on KNX / EIB bus	9.6 kbit/s		
KNX / EIB bus	Interface type	KNX / EIB (electrically isolated)		
	Transceiver	TP-UART		
	Bus current	5 mA		
	Baud rate	9.6 kbit/s		
	Bus topology: Refer to KNX / EIB manual	(Reference documentation, see below)		
Cable connections				
	Connection terminals for signals and power supply (plug-in screw terminals)	Solid or stranded conductors 0.25 ... 2.5 mm <sup>2</sup> or 2 x 1.5 mm <sup>2</sup>		
	KNX / EIB bus connection terminals (plug-in screw terminals)	Solid or stranded conductors 2 x max.1.0 mm <sup>2</sup> e.g. YCYM 2x2x0.8		
	Single cable lengths	For field devices, see also the RXB & RXL installation guide, CM110381		
	Signal inputs D1, D2	Max. 100 m with diameters ≥ 0.6 mm		
	Measured value input B1	Max. 100 m		
	AC24 V triac outputs , Y1 ... Y4	Max. 100m where A ≥ 1.5 mm <sup>2</sup>		
	Relay outputs Q14, Q24, Q34, Q44	Depends on load and local regulations		
	Interface to room unit	Max. 115 m where A= 0.75 mm <sup>2</sup> (including connecting cable for tool)		
	Cable type	4-core, twisted pair, unscreened		
	KNX / EIB bus	Max. 500 m		
	Cable type: Refer to KNX / EIB manual	(see "Reference documentation" below)		
	Tool connecting cable	Max. 3 m		
Housing protection standard				
	Protection standard to EN 60529	IP30 with terminal cover fitted and wall mounted without DIN rail IP20 for all other mounting arrangements		
Protection class				
Ambient conditions	Suitable for use in systems with protection class I or II			
	Normal operation	Class 3K5 to IEC 60721-3-3		
	Temperature	0 ... 50 °C		
	Humidity	< 85 % rh		
	Transport	Class 2K3 to IEC 60721-3-2		
	Temperature	- 25 ... 65 °C		
	Humidity	< 95 % rh		
Standards and directives				
	Product safety			
	Automatic electronic controls for household and similar use	EN 60730-1		
	General requirements for Home and Building Electronic Systems (HBES) and Building Automation and Control Systems	EN 50491-3		
	Electromagnetic compatibility			
	Immunity (industrial & domestic)	EN 60730-1		
	Emissions (domestic)	EN 60730-1		
	General requirements for Home and Building Electronic Systems (HBES) and Building Automation and Control Systems	EN 50491-5-3		
	Electronic individual zone control equipment	EN 15500		
 CE compliance				
	Meets requirements of EMC Directive	2004/108/EG		
	Low Voltage Directive	2006/95/EG		
 C-Tick conformity (EMC)		AS/NZS 61000-6-3		
Konnex compliance		Certified		
<b>eu.bac:</b> Meets the requirements for eu.bac certification				
	See product list at: <a href="http://www.eubaccert.org/licences-by-criteria.asp">http://www.eubaccert.org/licences-by-criteria.asp</a>			
	Type	License	Application	Control accuracy [K]
	RXB21.1/FC-10	20856	Fancoil 2 pipes	heating / cooling 0.2 / 0.1
			Fancoil 4 pipes	heating/ cooling 0.2 / 0.1
	RXB22.1/FC-12	20853	Fancoil 2 pipes	heating/ cooling 0.2 / 0.1
			Fancoil 2 pipes / 2 wires	heating/ cooling 0.2 / 0.1
 RoHS	Reduction of hazardous substances		2002/95/EC	

<b>Dimensions</b>	See dimension diagrams	
<b>Weight</b>	excluding packaging	0,640 kg
	including packaging	0,670 kg

Reference documentation	Building Services Management Manual – Fundamental principles, and ... – Applications Zentralverband Elektrotechnik- und Elektronikindustrie e.V. (ZVEH) (Central association for the electrical and electronic engineering industry), Stresemannallee 19D-60596 Frankfurt a. M, Germany.
-------------------------	---

## Connection terminals

### RXB21.1



3873408

#### Measured value input

- B1 1 Measured value input for LG-Ni 1000 sensors  
M 2 Measured value ground

#### Signal inputs

- D1 4 Signal input  
GND 5 Signal ground  
D2 6 Signal input

#### Triac outputs

- Y1 7 AC 24 V, 0.5 A switching output  
G 8 AC 24 V actuator supply  
Y2 9 AC 24 V, 0.5 A switching output  
Y3 10 AC 24 V, 0.5 A switching output  
G 11 AC 24 V actuator supply  
Y4 12 AC 24 V, 0.5 A switching output

#### Room unit

- CP- 13 PPS2 ground  
CP+ 14 PPS2 data  
CE+ 15 KNX / EIB data cable  
CE- 16 KNX / EIB data cable

#### KNX / EIB bus (plug-in connection)

- CE+ 17 KNX / EIB data cable  
CE- 18 KNX / EIB data cable

#### Power supply

- N 19 Neutral conductor  
R 21 Phase conductor AC 230 V +/- 10 %

#### Relay outputs


- Q13 25 Common feed for Q14, Q24 and Q34  
Q14 26 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 1)  
Q24 27 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 2)  
Q34 28 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 3)



- Observe the technical data for the relay outputs: max. AC 250 V, 5 (4) A
- Local installation regulations must be observed.

#### Tool socket


Proprietary RJ45-type tool socket



- |                              |                    |
|------------------------------|--------------------|
| 1 KNX / EIB data cable (CE+) | 5 +12VDC           |
| 2 KNX / EIB data cable (CE-) | 6 RxD              |
| 3 Not used                   | 7 PPS2 (CP+) / TxD |
| 4 Not used                   | 8 PPS2 (CP-)       |

## Connection terminals

### RXB22.1



#### Measured value input

B1 1 Measured value input for LG-Ni 1000 sensors

M 2 Measured value ground

#### Signal inputs

D1 4 Signal input

GND 5 Signal ground

D2 6 Signal input

#### Triac outputs

Y1 7 AC 24 V, 0.5 A switching output

G 8 AC 24 V actuator supply

Y2 9 AC 24 V, 0.5 A switching output

#### Room unit

CP- 13 PPS2 ground

CP+ 14 PPS2 data

CE+ 15 KNX / EIB data cable

CE- 16 KNX / EIB data cable

#### KNX / EIB bus (plug-in connection)

CE+ 17 KNX / EIB data cable

CE- 18 KNX / EIB data cable

#### Power supply

N 19 Neutral conductor

R 21 Phase conductor AC 230 V +/- 10 %

#### Relay outputs

Q13 25 Common feed for Q14, Q24 and Q34

Q14 26 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 1)

Q24 27 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 2)

Q34 28 Normally-open contact, max. AC 250 V, 5 (4) A (Stage 3)

Q43 23 Lead wire for Q44


Q44 21 N/O contact AC max. 250 V, 10 A... (electric heating coil)

#### Caution


- Observe the technical data for the relay outputs: Max. AC 250 V, 5 (4) A and 10 A, respectively
- Local installation regulations must be observed.

#### Tool socket

Proprietary RJ45-type tool socket



1	KNX / EIB data cable (CE+)	5	+12VDC
2	KNX / EIB data cable (CE-)	6	RxD
3	Not used	7	PPS2 (CP+) / TxD
4	Not used	8	PPS2 (CP-)



N1 / N2	RXB21.1 / RXB22.1
B1	LG-Ni 1000 temperature sensor
D1, D2	Volt-free contacts (window contact, occupancy sensor, etc.)
Y1...Y4	AC 24 V thermic valve actuators
Y1.1, Y3.1	Motorized AC 24 V, 3-position valve or damper actuator
Y1.2, Y2.2, Y3.2	Electromechanic AC 24 V, 2-position valve actuator
B2	QAX... room unit
Q1	3-speed fan
Q1.1	1-speed fan
Q2	Electric heating coil

Twisted pair



Note!

- Fans connected to relay outputs Q14 ... Q34 must not be operated in parallel. For parallel operation use cut-off relays or slave room controllers.
- At Q2 (1.8 kW max. resistive load), use additional external fuses of max. 10 A to protect the pcb tracks.

Note For information on the compatibility of field devices with the RXB21.1 and RXB22.1 room controller, refer to the various application descriptions (see the FNC description of functions, document CA110385)

**Parallel connection of several thermic valve actuators**


Up to two thermic actuators per sequence may be connected directly to the room controller. With more than two thermic actuators, a UA1T power amplifier is required.

The principle is the same for output Y2. Do not exceed the maximum simultaneous load on outputs Y1 and Y2 (max. 9.5 VA).


Power consumption at input X1 of the UA1T: 0.5 VA.



Connection to the controller



Connection to the power amplifier



N1 Room controller RXB21.1, RXB22.1

N2 UA1T power amplifier (see data sheet CA2N3591)

Y1 AC 24 V thermic valve actuators connected to the controller

Y1.x AC 24 V thermic valve actuators

(max. 2 STA72E / STP72E actuators per Y1 output on the UA1T)


Notes

- The UA1T requires an AC 24 V supply voltage
- The UA1T is *not* suitable for the connection of 3-position actuators.


## Dimensions

Dimensions in mm

### Without terminal cover



### With terminal covers



**Drilling diagram (1:1)**

